

CCTC P/N	DC-Bias 图表																				
TCC1210X5R476K160MT 16 V, 47 uF ±10%, X5R, 1210	<p style="text-align: center;">TCC1210X5R476K160MT-DC-Bias</p> <p>This graph plots the relative change in capacitance ($\Delta C/C (\%)$) against DC voltage (V). The x-axis ranges from 0 to 16 V, and the y-axis ranges from -90% to 0%. The curve shows a monotonic decrease in capacitance as the DC voltage increases, starting at 0% at 0 V and reaching approximately -85% at 16 V.</p> <table border="1"> <thead> <tr> <th>DC (V)</th> <th>$\Delta C/C (\%)$</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td></tr> <tr><td>2</td><td>-10</td></tr> <tr><td>4</td><td>-25</td></tr> <tr><td>6</td><td>-45</td></tr> <tr><td>8</td><td>-55</td></tr> <tr><td>10</td><td>-65</td></tr> <tr><td>12</td><td>-70</td></tr> <tr><td>14</td><td>-75</td></tr> <tr><td>16</td><td>-80</td></tr> </tbody> </table>	DC (V)	$\Delta C/C (\%)$	0	0	2	-10	4	-25	6	-45	8	-55	10	-65	12	-70	14	-75	16	-80
DC (V)	$\Delta C/C (\%)$																				
0	0																				
2	-10																				
4	-25																				
6	-45																				
8	-55																				
10	-65																				
12	-70																				
14	-75																				
16	-80																				
TCC1206X5R476M160HT 16 V, 47 uF ±20%, X5R, 1206	<p style="text-align: center;">TCC1206X5R476M160HT-DC-Bias</p> <p>This graph plots the relative change in capacitance ($\Delta C/C (\%)$) against DC voltage (V). The x-axis ranges from 0 to 16 V, and the y-axis ranges from -90% to 0%. The curve shows a monotonic decrease in capacitance as the DC voltage increases, starting at 0% at 0 V and reaching approximately -85% at 16 V.</p> <table border="1"> <thead> <tr> <th>DC (V)</th> <th>$\Delta C/C (\%)$</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td></tr> <tr><td>2</td><td>-15</td></tr> <tr><td>4</td><td>-30</td></tr> <tr><td>6</td><td>-50</td></tr> <tr><td>8</td><td>-60</td></tr> <tr><td>10</td><td>-70</td></tr> <tr><td>12</td><td>-75</td></tr> <tr><td>14</td><td>-80</td></tr> <tr><td>16</td><td>-85</td></tr> </tbody> </table>	DC (V)	$\Delta C/C (\%)$	0	0	2	-15	4	-30	6	-50	8	-60	10	-70	12	-75	14	-80	16	-85
DC (V)	$\Delta C/C (\%)$																				
0	0																				
2	-15																				
4	-30																				
6	-50																				
8	-60																				
10	-70																				
12	-75																				
14	-80																				
16	-85																				
TCC1206X5R107K6R3HT 6.3 V, 100 uF ±10%, X5R, 1206	<p style="text-align: center;">TCC1206X5R107K6R3HT-DC-Bias</p> <p>This graph plots the relative change in capacitance ($\Delta C/C (\%)$) against DC voltage (V). The x-axis ranges from 0 to 6.3 V, and the y-axis ranges from -80% to 10%. The curve shows a peak in capacitance around 1.26 V before decreasing as the DC voltage increases, reaching approximately -75% at 6.3 V.</p> <table border="1"> <thead> <tr> <th>DC (V)</th> <th>$\Delta C/C (\%)$</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td></tr> <tr><td>1.26</td><td>8</td></tr> <tr><td>2.52</td><td>-25</td></tr> <tr><td>3.78</td><td>-50</td></tr> <tr><td>5.04</td><td>-60</td></tr> <tr><td>6.3</td><td>-75</td></tr> </tbody> </table>	DC (V)	$\Delta C/C (\%)$	0	0	1.26	8	2.52	-25	3.78	-50	5.04	-60	6.3	-75						
DC (V)	$\Delta C/C (\%)$																				
0	0																				
1.26	8																				
2.52	-25																				
3.78	-50																				
5.04	-60																				
6.3	-75																				
TCC1210X5R107M6R3MT 6.3 V, 100 uF ±20%, X5R, 1210	<p style="text-align: center;">TCC1210X5R107M6R3MT-DC-Bias</p> <p>This graph plots the relative change in capacitance ($\Delta C/C (\%)$) against DC voltage (V). The x-axis ranges from 0 to 6.3 V, and the y-axis ranges from -60% to 20%. The curve shows a peak in capacitance around 1.26 V before decreasing as the DC voltage increases, reaching approximately -55% at 6.3 V.</p> <table border="1"> <thead> <tr> <th>DC (V)</th> <th>$\Delta C/C (\%)$</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td></tr> <tr><td>1.26</td><td>8</td></tr> <tr><td>2.52</td><td>-10</td></tr> <tr><td>3.78</td><td>-30</td></tr> <tr><td>5.04</td><td>-40</td></tr> <tr><td>6.3</td><td>-55</td></tr> </tbody> </table>	DC (V)	$\Delta C/C (\%)$	0	0	1.26	8	2.52	-10	3.78	-30	5.04	-40	6.3	-55						
DC (V)	$\Delta C/C (\%)$																				
0	0																				
1.26	8																				
2.52	-10																				
3.78	-30																				
5.04	-40																				
6.3	-55																				